

SAS-203-47042-F1

Linear to Circular Polarizer, K Band, 17.5 to 22 GHz

SAS-203-47042-F1 is a K band, linear to circular polarizer that operates from 17.5 to 22 GHz. The polarizer offers a typical insertion loss of 0.5 dB, a typical axial ratio of 1.1, and a typical return loss of 17 dB. The polarizer is fixed and can be used for either right-handed or left-handed polarization based on the direction of the input signal. The polarizer input and output port is a 0.470" diameter waveguide with UG-595/U-M flange. The polarizer is often combined with Eravant's rectangular to circular waveguide transition ([SWT-42470-SA](#)) and WR-42 conical horn antenna ([SAC-2309-470-S2](#)) for various system applications.



Electrical Specifications:

Parameter	Minimum	Typical	Maximum
Frequency Range	17.5 GHz		22 GHz
Insertion Loss		0.5 dB	
Axial Ratio		1.1	
Return Loss		17 dB	
Specification Temperature		+25°C	
Operating Temperature	-40°C		+85°C

Mechanical Specifications:

Item	Specification
Waveguide	Ø0.470" Circular Waveguide with UG-595/U-M Flange
Length	2.0"
Case Material	Aluminum
Finish	Gold Plated
Weight	0.9 Oz
Outline	AS-FKB-470

ECCN

EAR99

FEATURES

- Circular Waveguide Interface
- Low Insertion Loss
- Good Axial Ratio


APPLICATIONS

- Antenna Ranges
- Waveguide Polarization Selection
- Radar Systems
- Communication Systems


SUPPLEMENTAL DETAILS



Typical Performance vs Frequency



Mechanical Outline: (Unless otherwise specified, all dimensions are in inches [millimeters])



NOTE:

- The polarizer is offered as LHCP. However, it can be used as RHCP by reversing the input and output ports.
- On condition that test data is provided it is collected from a sample lot. Actual data may vary slightly from unit to unit. All testing is performed under +25 °C room temperature.
- On condition that simulated test data is provided, actual measured data may slightly vary.
- Eravant reserves the right to change the information presented without notice.

CAUTION:

- If a waveguide is present, any foreign objects in the waveguide will cause performance degradation and may damage or destroy the unit.

LHCP and RHCP Polarization Configuration Notes and Diagram:

- The polarizer's product label indicates the direction of **Left-Handed Circular Polarization (LHCP)**.
- An example configuration diagram is provided below. The diagram indicates the input and output ports and the orientation in which the polarizer is to be attached to the rest of the components to obtain a **LHCP** signal at the output port.
- The polarizer can be configured to obtain a **Right-Handed Circular Polarized (RHCP)** signal at the output port by reversing the input and output ports as shown in the second diagram.

