

## RECTANGULAR WAVEGUIDES

Band	Designator	Inner Dia.(mm)	Frequency	Wavelength	Flanges
K	WR42	10.668x4.318	18-26.5GHz	16.6-11.3mm	UG-595/U
A	WR28	7.112x3.556	26.5-40GHz	11.3-7.5mm	UG-599/U
B	WR22	5.690x2.845	33-50GHz	9.1-6.0mm	UG-383/U
U	WR19	4.775x2.388	40-60GHz	7.5-5.0mm	UG-383/UM
V	WR15	3.759x1.880	50-75GHz	6.0-4.0mm	UG-385/U
E	WR12	3.099x1.549	60-90GHz	5.0-3.3mm	UG-387/U
W	WR10	2.540x1.270	75-110GHz	4.0-2.7mm	UG-387/UM
n/a	WR9	n/a	82.5-125GHz	n/a	UG-387/UM
F	WR8	2.032x1.016	90-140GHz	3.3-2.1mm	UG-387/UM
D	WR6.5	1.651x0.826	110-170GHz	2.7-1.8mm	UG-387/UM
G	WR5.1	1.295x0.648	140-220GHz	2.1-1.4mm	UG-387/UM
H	WR4.3	1.092x0.546	170-260GHz	n/a	UG-387/UM
J	WR3.4	0.864x0.432	220-330GHz	n/a	UG-387/UM
n/a	WR2.8	0.711x0.356	260-400GHz	n/a	UG-387/UM
n/a	WR2.2	0.559x0.279	330-500GHz	n/a	UG-387/UM
n/a	WR1.9	0.483x0.241	400-600GHz	n/a	UG-387/UM
n/a	WR1.5	0.381x0.191	500-750GHz	n/a	UG-387/UM
n/a	WR1.2	0.305x0.152	600-900GHz	n/a	UG-387/UM
n/a	WR1.0	0.254x0.127	750-1100GHz	n/a	n/a
n/a	WR0.8	0.203x0.102	900-1400GHz	n/a	n/a
n/a	WR0.65	0.165x0.083	1100-1700GHz	n/a	n/a
n/a	WR0.51	0.130x0.065	1400-2200GHz	n/a	n/a

日本総販売代理店



株式会社 アムテックス

〒156-0052

東京都世田谷区経堂5丁目20番16号