

GAJT-AE-N

GPS Anti-Jam Technology (GAJT) Antenna Electronics for smaller platforms



Jamming and interference are constant threats

Jamming and interference, whether intentional or unintentional, can seriously degrade GNSS position, navigation and timing (PNT) availability—even to the point of total solution denial. Jammers create excessive noise, overpowering the low power GNSS signals and saturating the electronics in a GNSS receiver front end. Methods are needed to suppress this interference so your GNSS receiver continues to operate.

Battle-proven small and light enclosure

GAJT-AE-N is the antenna electronics for a Controlled Reception Pattern Antenna (CRPA) in a rugged enclosure which enables easy connectivity. GAJT-AE-N is designed for size and weight constrained applications such as small airborne and ground unmanned platforms, where it may be preferable to mount the antenna electronics inside the vehicle. Users can select from a variety of 4-element CRPA antenna arrays.

How it works

GAJT-AE-N mitigates interference by creating nulls in the antenna gain pattern in the direction of the jammers, providing significant anti-jam protection even in dynamic multi-jammer environments. The output is a protected standard Radio Frequency (RF) signal, free from jamming and suitable for input into modern and legacy GNSS receivers.

Leading-edge technology

Interference mitigation is achieved by applying proprietary digital null forming algorithms to the signals, creating dynamic nulls to give protection against narrowband and broadband interference sources. The unit comprises Radio Frequency (RF) front ends and null forming electronics. Integration to your GNSS receiver is seamless; DC power supply and data output are made via a dedicated LEMO® connector. We recommend CRPA antennas from Antcom Corporation for use with the GAJT-AE-N.

Protects GNSS navigation and precise timing receivers

GAJT-AE-N protects GPS L1/L2, QZSS L1/L2, SBAS L1 and Galileo E1 signals. The wide bandwidth of GAJT ensures compatibility with M-Code GPS.

Benefits

- Commercial off-the-shelf (COTS)
- Low cost anti-jam protection for small platforms
- Easy to integrate
- Anti-jam protection in dynamic multi-jammer scenarios
- Compatible with legacy and modern GNSS receivers, including M-Code
- Works with most 4-element antenna arrays (supplied separately)

Features

- Affordable protection for GNSS position, velocity and timing
- 40 dB of interference suppression
- Simultaneous GPS L1/L2, QZSS L1/L2, SBAS L1 and Galileo E1 protection
- Supports M-Code on GPS L1 & L2
- Adaptive digital nulling
- Built in test and jamming status included in RS-232 output

Performance

GNSS Signals

Center frequency	
GPS L1, QZSS L1, SBAS L1	1575.42 MHz ±12 MHz
GPS L2, QZSS L2	1227.6 MHz ±12 MHz
Galileo E1	1575.42 MHz ±12 MHz

Interference Rejection

Simultaneous L1/E1 and L2

Typical wideband suppression	40 dB
Number of simultaneous nulling directions	3

Antenna Array Options

L1 and L2

- 4NF-5.5CG1215P 4 element CRPA family
- For additional options, please contact NovAtel

RF Ports

RF inputs	4 x 50 ohm SMA
RF outputs	1 x 50 ohm SMA

Power & Communication Port

1 LEMO connector for both RS-232 field loading and DC power

Physical and Electrical

Power

Power consumption	15 W
Input voltage	+10 to +32 VDC

RF Performance

Active Gain	40 dB
-------------	-------

GAJT-AE-N (Enclosure)

Dimensions	179.5 × 155.5 × 39 mm
Weight	1200 g

Environmental

MIL-STD-810G

Temperature

Operating	-40°C to +71°C
Storage	-55°C to +85°C

Humidity 95% non-condensing

Vibration MIL-STD-810G(CH1), 514.7

Shock MIL-STD-810G(CH1), 516.7

Enclosure

Immersion MIL-STD-810G(CH1), 512.6

Blowing Rain MIL-STD-810G(CH1), 506.6

Water Jets IEC 60529 IPX6

Timing

Fixed timing delay

Accessories

- Power and data cable, included

Export Approvals

Canadian Controlled Goods

GAJT Products

GAJT-710 series



- Single enclosure system for land and fixed applications
- 7-element antenna array
- Easy to integrate, ideal for retrofitting
- **GAJT-710ML**
Land vehicles and fixed installations
- **GAJT-710MS**
Warships and other marine vessels and coastal applications

GAJT-410ML



- Compact enclosure system for land and fixed applications
- 4-element antenna array
- Direction finding and jammer status
- Available in Olive Drab or Desert Tan
- Also available in white (GAJT-410MS)

4-Element Antenna Array

A 4-element antenna array allows gain pattern shapes to be changed in response to interference. Provides 3 independent nulls.



Contact Hexagon | NovAtel

sales.nov.ap@hexagon.com 1-800-NOVATEL (U.S. and Canada) or 403-295-4900 | China: 0086-21-68882300 | Europe: 44-1993-848-736 | SE Asia and Australia: 61-400-883-601. For the most recent details of this product: novatel.com

GAJT and NovAtel are trademarks of NovAtel, Inc., entities within the Hexagon Autonomy & Positioning division, their affiliated entities, and/or their licensors. All other trademarks are properties of their respective owners.

©2021 NovAtel Inc. All rights reserved. NovAtel is part of Hexagon. NovAtel makes no representation or warranty regarding the accuracy of the information in this publication. This document gives only a general description of the product(s) or service(s) offered by NovAtel, and, except where expressly provided otherwise, shall not form part of any contract. Such information, the products and conditions of supply are subject to change without notice.

D17449 Version 2 | 13 May 2021 | Printed in Canada